

07/18/00

JC715 U.S. PTO

UTILITY PATENT APPLICATION TRANSMITTAL

(Only for new nonprovisional applications under 37 CFR 1.53(b))

Attorney Docket No. 1417-180A Total Pages

First Named Inventor or Application Identifier James D.Y. COLLIER et al.

Express Mail Label No.

JC869 U.S. PTO 09/18/96

07/18/00

APPLICATION ELEMENTS See MPEP chapter 600 concerning utility patent application contents.	ADDRESS TO: Assistant Commissioner of Patents Box Patent Application Washington, D.C. 20231
1. <input type="checkbox"/> Fee Transmittal Form (Submit an original, and a duplicate for fee processing) 2. <input checked="" type="checkbox"/> Specification Total pages [18] (preferred arrangement set forth below) - Descriptive title of the invention - Cross references to Related Applications - Statement Regarding Fed sponsored R&D - Reference to Microfiche Appendix - Background of the Invention - Brief Summary of the Invention - Brief Description of the Drawings - Detailed Description - Claims - Abstract of the Disclosure 3. <input checked="" type="checkbox"/> Drawing(s) (35 USC 113) (Total Sheets) [2] 4. <input type="checkbox"/> Oath or Declaration (Total Pages) [a. <input type="checkbox"/> Newly executed (original or copy) b. <input type="checkbox"/> Copy from a prior application (37 CFR 1.63(d) (for continuation/divisional with Box 17 completed) [Note Box 5 below] i <input type="checkbox"/> DELETION OF INVENTOR(S) Signed statement attached deleting inventor(s) named in the prior application, see 37 CFR 1.63(d)(2) and 1.33(b) 5. <input type="checkbox"/> Incorporation by Reference (useable if Box 4b is checked) The entire disclosure of the prior application, from which a copy of the oath or declaration is supplied under Box 4b, is considered as being part of the disclosure of the accompanying application and is hereby incorporated by reference therein.	6. <input type="checkbox"/> Microfiche Computer Program (Appendix) 7. Nucleotide and/or Amino Acid Sequence Submission (if applicable, all necessary) a. <input type="checkbox"/> Computer Readable Copy b. <input type="checkbox"/> Paper Copy (identical to computer copy) c. <input type="checkbox"/> Statement verifying identity of above copies ACCOMPANYING APPLICATION PARTS 8. <input type="checkbox"/> Assignment Papers (cover sheet & document(s)) 9. <input type="checkbox"/> 37 CFR 3.73(b) Statement (when there is an assignee) <input type="checkbox"/> Power of Attorney 10. <input type="checkbox"/> English Translation Document (if applicable) 11. <input type="checkbox"/> Information Disclosure Statement /PTO 1449 <input type="checkbox"/> Copies of IDS Citations 12. <input type="checkbox"/> Preliminary Amendment 13. <input checked="" type="checkbox"/> Return Receipt Postcard (MPEP 503) (Should be specifically itemized) 14. <input type="checkbox"/> Small Entity Statement(s) <input type="checkbox"/> Statement Filed in prior application, Status still proper and desired 15. <input type="checkbox"/> Certified Copy of Priority Document(s). (if foreign priority is claimed) 16. <input type="checkbox"/> Other:

17. If a CONTINUING APPLICATION, check appropriate box and supply the requisite information:
☐ Continuation ☐ Divisional ☐ Continuation-in-part (CIP) of prior application No.:

18. CORRESPONDENCE ADDRESS

☐ Customer Number or Bar Code Label or ☒ Correspondence address below
(Insert Customer No. or Attach bar code label here)

Name	Vincent M. DeLuca, Reg. No. 32,408 Vincent M DeLuca				
Address	Rothwell, Figg, Ernst & Manbeck Suite 701-East, 555 13th Street, N.W.				
City	Washington	State	D.C.	Zip Code	20004
Country	U.S.A.	Telephone	202-783-6040	Fax	202-783-6031

FIELD OF THE INVENTION

BACKGROUND OF THE INVENTION

In many applications of oscillators such as the one shown in figure 1 there is a need to arrange the oscillator accurately so that a pre-defined range of frequencies can then be tuned over exactly using the varicap diodes 107, 108. For example, in many communications applications the oscillator may be required to operate at one of a number of pre-defined frequencies that correspond to the frequencies of available communication channels. In order for the communications terminal that uses the oscillator to establish communication with another terminal the frequencies used by the two terminals must match each other precisely. In production there is often significant variation between the values of the circuit components between individual oscillators. This is especially significant when the oscillator is built on-chip. (Typical variation in the values of on-chip components are: $\pm 30\%$ for resistors, $\pm 10\%$ for capacitors and $\pm 7\%$ for inductors; the values also being strongly dependant on temperature). Therefore, it is

common for the oscillator to be trimmed after production so that the pre-determined channel frequencies can then each be selected by applying a corresponding channel-setting voltage at the control input 109.

One way to perform the trimming operation is by using the varicap diodes 107, 108 themselves. A trimming offset voltage can be applied to the control input 109 to ensure that when the channel-setting voltages are also applied to the control input 109 the pre-determined channel frequencies are generated accurately. However, this approach requires the varicap diodes to have sufficient throw (range) to be capable of adjusting the resonant frequency not just over the frequency envelope of the available channels but also over an additional range to cope with the need for trimming the circuit. The required total throw is typically around 30%. The effect of this is that, compared to one of smaller throw, the varicap diode is more sensitive to the voltage at the control input 109. As a result, in normal operation it is more difficult to control the varicap diode accurately. Furthermore, the wide pull range implies that much of the oscillation energy of the circuit passes via the varicap diodes 107, 108, which typically have much higher losses (i.e. lower Q) than fixed value capacitors. High loss causes poor phase noise, which substantially degrades the performance of radio receivers, which are a common application of variable oscillators. Another problem is that if the varicap diode has a large throw then the variation in voltage at the control input 9 as a result of the oscillation can itself alter the capacitance of the varicap and therefore modulate the frequency of the circuit. In addition, where the oscillator is used with a phase-locked loop (PLL) the wide range of effective capacitance of the varicaps 107, 108 means that the loop gain of the PLL is subject to variation. This results in poor settling, which is not compatible with the rapid jumps needed for frequency hopping systems. Although this can be addressed by introducing an adjustment for the loop time constant, this is an expensive operation during manufacture.

Another approach is to use the circuit of figure 2. In figure 2 like components are numbered as for figure 1. In the circuit of figure 2 an additional mechanical trimmer 110 is provided in the capacitive portion 105 of the oscillator. This allows a varicap diode of smaller throw to be used. However, the mechanical trimmer is bulky, relatively expensive and requires an inconvenient step of mechanical adjustment during production. As an alternative to a mechanical trimmer the capacitance 110 could be provided by a monolithic capacitor that can be adjusted during production by laser trimming. However, this approach is inconvenient because it can only be done before the monolithic component is packaged, and expensive because the laser trimming step has a low yield and is incompatible with conventional integrated circuit (IC) processes.

In another known arrangement the continuously variable capacitance unit (e.g. represented by varicaps 107, 108 in figure 1) are arranged in parallel with a finitely variable capacitance arrangement which is capable of capacitance steps just a little smaller than the sweep range of the finitely variable capacitance. With this arrangement a first coarse tuning operation can be carried out after manufacture using the finitely variable capacitance arrangement to bring desired capacitances within the sweep range of the continuously variable capacitance. The setting of the finitely variable arrangement is then fixed. Then during use the continuously variable capacitance can be adjusted to give precisely the desired capacitance. However, the coarseness of the first tuning operation means that the continuously variable capacitance frequently has to operate substantially outside its optimum range.

There is a need for a variable frequency oscillator that can be trimmed more easily and economically, without significant deterioration in performance.

SUMMARY OF THE INVENTION

According to one aspect of the present invention there is provided a variable frequency oscillator comprising: an oscillatory circuit for generating a periodic

According to a second aspect of the present invention there is provided a variable frequency oscillator comprising: an oscillatory circuit for generating a periodic output dependant on the capacitance between a first node and a second node of the circuit, and having a capacitive element connected between the first node and the second node; the capacitive element comprising: a variable capacitance unit, the capacitance of which is variable for continuously varying the frequency of the output over a frequency range; and a plurality of trimming capacitances each being selectively connectable in series with the capacitive element to trim the frequency of the output in steps of less than half the width of the said frequency range.

The plurality of trimming capacitances preferably provide a finitely variable capacitance unit. The trimming capacitances are suitably selectively connectable in parallel with each other.

The oscillator may comprise control apparatus for causing a set of the trimming capacitances to be connected between the first node and the second node. The oscillator may also comprise a memory coupled to the control apparatus for storing information defining one or more sets of the trimming capacitances. The control apparatus and/or the memory may also perform other functions in any device of which the oscillator forms part. Each of the said one or more sets may correspond to a respective operating frequency of the oscillator. The control apparatus may be capable of retrieving the information defining one of the sets in response to information defining an operating frequency being supplied to the control apparatus. The control apparatus may be capable of retrieving from the memory information defining one of the sets and then causing that set of the trimming capacitances to be connected between the first node and the second node.

At least one of the trimming capacitances may have a different capacitance value from another of the trimming capacitances. Preferably all of their values are different.

The trimming capacitances are preferably capable of trimming the frequency of the output in steps of less than half, and most preferably less than a tenth of the width of the frequency range over which the continuously variable capacitive element is by itself capable of providing adjustment. The trimming capacitances preferably provide for more than 10 and most preferably more than 40 or 50 finite adjustment steps.

The capacitance of the variable capacitance unit may be variable by means of the voltage applied to an input of the variable capacitance. There may be feedback apparatus such as a phase-locked loop connected between the output and the variable capacitance input for stabilising the oscillator. The variable capacitance unit is preferably continuously variable.

008120 96281960

100

BRIEF DESCRIPTION OF THE DRAWINGS

figure 3 shows the circuit of a variable frequency oscillator; and figure 4 shows a control arrangement for the circuit of figure 3.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Figure 3 shows a variable oscillator circuit for a radio terminal, which can be implemented on a single integrated circuit. The variable oscillator circuit shown in figure 3 comprises a resonant section 1 and an amplification stage 3. The resonant section includes a capacitive section indicated generally at 5 and 6 and an inductive section 7. In the circuit of figure 3 the capacitive sections include an array of switchable trimming capacitances 10, 11, 12 and 13, 14, 15

which can be selectively switched into the resonant circuit by respective transistors 22, 23, 24 and 19, 20, 21 to allow the circuit to be trimmed digitally.

In more detail, the resonant section of figure 3 includes an inductance 7 connected between the input node 4 and the output node 2 of the amplification section. The capacitors 10-12 are connected in parallel between node 4 and signal ground. In series with each capacitor 10-12 is a respective switching transistor 16-18. Each switching transistor is connected so that when a suitable voltage is applied to its gate from the corresponding switching input line 22-24 current can flow between its source and drain so that the capacitor with which it is connected in series is coupled between node 4 and signal ground. A variable capacitance branch is connected between node 4 and signal ground. Identical circuitry is connected to node 2, comprising capacitors 13, 14 and 16 and associated transistors 19, 20 and 21.

After the circuit has been manufactured on-chip it can be trimmed by switching one or more of the capacitors 10-15 etc. fully into or out of the circuit and thereby altering the effective capacitance of the whole resonant section 1 of the oscillator.

The trimming of the circuit could be performed each time the terminal is turned on, for example by comparing the output of the circuit with a standard received frequency. Alternatively, the trimming operation could be performed at the manufacture stage. Since each trimming capacitance is switched fully into or out of the circuit the trimming is a digital operation. The setting of the switching transistors 16-21 etc. can be represented as a binary number with one digit corresponding to the switching input to each switching transistor. The setting of the trimming capacitors can therefore be stored digitally by memory of the radio terminal during manufacture or use and reproduced exactly when required by recalling the appropriate setting from memory. More than one setting could be stored (either at manufacture or during use) for different applications, such as different operating frequencies or temperatures.

The control unit 28 could retrieve preferred settings for the switching inputs 22-27 etc. at each operating frequency from memory 30. To switch frequencies the control unit could then apply the stored settings to the inputs 22-27 and leave the analogue PLL to settle any residual frequency error. In this arrangement there could be no need for the control unit to influence the voltage on input 9 directly, so the oscillator control could be fully digital. The combined setting of the inputs 22-27 etc. could be viewed as a multi-bit binary trimming set signal from control unit 28.

1. Apply to the switching inputs the digital code stored in the look-up table for an operating frequency.
2. Wait for the PLL to stabilise.
3. Digitise the voltage at the varicap input 9 by means of an A-D converter in the control unit 28.

- This method could also be used during a built-in self-test (BIST) operation in the terminal. The above method could be cycled through for each operating frequency. A self-test feature of this type can yield significant cost savings during production and is desirable for ensuring proper operation during use.

The array of capacitors may include any number of capacitors from two upwards. The values of the trimming capacitors could be the same or different. If the values of the trimming capacitors are different then the same number of trimming capacitors can be used to allow trimming over a wider range, saving on IC real estate. The trimming capacitors could suitably provide 128 equal steps of total capacitance. This could, for instance, be achieved by 128 capacitors of the same value, or 7 capacitors of values scaled factors of two apart.

Step 5 of the algorithm set out above is especially beneficial because it allows for gradual changes to counteract drifts (due, for instance, to temperature fluctuations) without the need for full re-calibration.

The finitely adjustable portion of the capacitive section preferably allows around 50 or more finite capacitance steps, with a step size substantially smaller than the range of the varicap. This allow the varicap to be not just pulled into range at a selected finite step, but to be arranged so that a desired narrow part of its continuously variable range will yield the desired capacitance. This provides better control of loop time constant and loop response compared to a system in which at only one step setting can the varicap give the desired overall capacitance.

The range of the continuously variable capacitance (in this example the varicap) preferably provides for frequency adjustment over a very much smaller range than the total range of variation available from the capacitive section including also the finitely variable capacitance circuitry. This provides much better phase noise

performance than a system in which the continuously variable capacitance accounts for a major proportion of the total adjustment range.

The radio terminal could be a radio transmitter and/or receiver. The terminal could operate according to any suitable scheme, including TDMA (time division multiple access) and FHSS (frequency hopped spread spectrum). The oscillator could be used in other applications such as tone generation.

Numerous changes could be made to the circuits shown in figures 3 and 4. For example, the output stage of the oscillator could be varied as required. The varicaps 7, 8 could be replaced or supplemented by one or more other forms of voltage, current or manually controlled capacitance, or only one variable capacitance section used, rather than the symmetric example shown in figure 3.

The applicant draws attention to the fact that the present invention may include any feature or combination of features disclosed herein either implicitly or explicitly or any generalisation thereof, without limitation to the scope of any of the present claims. In view of the foregoing description it will be evident to a person skilled in the art that various modifications may be made within the scope of the invention.

1. A variable frequency oscillator comprising:

a variable capacitance unit, the capacitance of which is variable for varying the frequency of the output; and

2. A variable oscillator as claimed in claim 1, wherein the trimming capacitances are each selectively connectable between the first node and the second node.

3. A variable oscillator as claimed in claim 1, wherein the trimming capacitances are each selectively connectable in parallel with each other.

4. A variable oscillator as claimed in claim 1, wherein a switch is connected in series with each trimming capacitance between the first node and the second node for selectively connecting the respective trimming capacitance between the first node and the second node in response to a respective switching signal.

5. A variable oscillator as claimed in claim 4, wherein each switch is a switching transistor.

6. A variable oscillator as claimed in claim 1, comprising control apparatus for causing a set of the trimming capacitances to be connected between the first node and the second node.

7. A variable oscillator as claimed in claim 6, wherein the control apparatus is capable of generating the said switching signals.
8. A variable oscillator as claimed in claim 6, comprising a memory coupled to the control apparatus for storing information defining one or more sets of the trimming capacitances.
9. A variable oscillator as claimed in claim 8, wherein each of the said one or more sets corresponds to a respective operating frequency of the oscillator.
10. A variable oscillator as claimed in claim 8, wherein the control apparatus is capable of retrieving from the memory information defining a set of the trimming capacitances and causing that set of the trimming capacitances to be connected between the first node and the second node.
11. A variable oscillator as claimed in claim 1, wherein at least one of the trimming capacitances has a different capacitance value from another of the trimming capacitances.
12. A variable oscillator as claimed in claim 1, wherein the capacitance of the variable capacitance unit is variable by means of the voltage applied to a variable capacitance input.
13. A variable oscillator as claimed in claim 12, comprising feedback apparatus connected between the output and the variable capacitance input for stabilising the oscillator.
14. A variable oscillator as claimed in claim 13, wherein the feedback apparatus is a phase-locked loop.

15. A variable oscillator as claimed in claim 1, wherein the variable capacitance unit is a variable capacitance diode.
16. A radio terminal comprising a variable oscillator as claimed in claim 1.
17. A method for operating a variable frequency oscillator as claimed in claim 12, the method comprising:
- retrieving from the memory information defining a set of the trimming capacitances;
 - connecting that set of the trimming capacitances between the first node and the second node;
 - comparing the voltage at the variable capacitance input with a first preset voltage range; and
 - if that voltage is outside the first preset voltage range determining, based on the voltage at the variable capacitance input, an adjusted set of the trimming capacitances and storing in the memory information defining that adjusted set of the trimming capacitances.
18. A method as claimed in claim 17, wherein the said step of determining is performed only if the voltage at the variable capacitance input is inside a second preset voltage range.
19. A method as claimed in claim 17, wherein, in the step of storing, the information defining the adjusted set of the trimming capacitances is stored so as to replace in the memory the said information defining a set of the trimming capacitances.
20. A variable frequency oscillator comprising:
- an oscillatory circuit for generating a periodic output dependant on the capacitance between a first node and a second node of the circuit, and having a capacitive element connected between the first node and the second node;

a variable capacitance unit, the capacitance of which is variable for continuously varying the frequency of the output over a frequency range; and

21. A variable oscillator as claimed in claim 20, wherein the variable capacitance unit is connected between the first node and an intermediate node, and the trimming capacitances are each selectively connectable in series with the variable capacitance unit between the intermediate node and the second node.

23. A variable oscillator as claimed in claim 20, wherein a switch is connected in series with each trimming capacitance between the intermediate node and the second node for selectively connecting the respective trimming capacitance between the intermediate node and the second node in response to a respective switching signal.

25. A variable oscillator as claimed in claim 20, comprising control apparatus for causing a set of the trimming capacitances to be connected between the first node and the second node.

26. A variable oscillator as claimed in claim 25, wherein the control apparatus is capable of generating the said switching signals.

27. A variable oscillator as claimed in claim 25, comprising a memory coupled to the control apparatus for storing information defining one or more sets of the trimming capacitances.

28. A variable oscillator as claimed in claim 27, wherein each of the said one or more sets corresponds to a respective operating frequency of the oscillator.

29. A variable oscillator as claimed in claim 27, wherein the control apparatus is capable of retrieving from the memory information defining a set of the trimming capacitances and causing that set of the trimming capacitances to be connected between the first node and the second node.

30. A variable oscillator as claimed in claim 20, wherein at least one of the trimming capacitances has a different capacitance value from another of the trimming capacitances.

31. A variable oscillator as claimed in claim 20, wherein the capacitance of the variable capacitance unit is variable by means of the voltage applied to a variable capacitance input.

32. A variable oscillator as claimed in claim 31, comprising feedback apparatus connected between the output and the variable capacitance input for stabilising the oscillator.

33. A variable oscillator as claimed in claim 32, wherein the feedback apparatus is a phase-locked loop.

34. A variable oscillator as claimed in claim 20, wherein the variable capacitance unit is a variable capacitance diode.

35. A radio terminal comprising a variable oscillator as claimed in claim 20.

36. A method for operating a variable frequency oscillator as claimed in claim 31, the method comprising:

retrieving from the memory information defining a set of the trimming capacitances;

connecting that set of the trimming capacitances between the first node and the second node;

comparing the voltage at the variable capacitance input with a first preset voltage range; and

if that voltage is outside the first preset voltage range determining, based on the voltage at the variable capacitance input, an adjusted set of the trimming capacitances and storing in the memory information defining that adjusted set of the trimming capacitances.

37. A method as claimed in claim 36, wherein the said step of determining is performed only if the voltage at the variable capacitance input is inside a second preset voltage range.

38. A method as claimed in claim 36, wherein, in the step of storing, the information defining the adjusted set of the trimming capacitances is stored so as to replace in the memory the said information defining a set of the trimming capacitances.

ABSTRACT**VARIABLE OSCILLATOR**

A variable frequency oscillator comprising: an oscillatory circuit for generating a periodic output dependant on the capacitance between a first node and a second node of the circuit, and having a capacitative element connected between the first node and the second node; the capacitative element comprising: a variable capacitance unit, the capacitance of which is variable for varying the frequency of the output; and a plurality of finite capacitances each being selectively connectable in parallel with the variable capacitance unit between the first node and the second node to trim the frequency of the output.

Figure 3

008720-95287960

Fig. 1




Fig. 2






Fig. 3



2
2

Fig. 4



008740 95287960